

# ZAP Controls

840 Plug In Receiver/2416 Internal Antenna/2414 External Antenna

## ZAP Part# 840

### Description:

Zap plug-in radio receiver with signal light.

### Wiring requirements:

None

### Power requirement:

None

### Mounting type:

Plug in

### Programming:

Program button on main control panel.

### Operating temp:

-13 deg F to + 149 deg F

### Works with:

871-FS

8855 Turbo drive Fire Station model to facilitate Auto-close Fire Station programming

### Operating frequency:

433.92 Mhz.

### Number of transmitters accepted:

Up to 60 Zap Transmitters on commercial models  
825 3.0/8825 3.0. Up to 10 ZAP transmitters on other models.

### Antennas

#### Internal: Model 2416

Plug-in internal antenna for standard use. The 2416 is not recommended for use where there is a steel building or a lack of windows.

### Mounting type:

Plug in

### Terminal plug:

2 Position Dual Direction slide in plug

### Operating temp:

-13 deg F to + 149 deg F

840



2416



2414



### External: Model 2414

Wall mounting case with external adjustable direction antenna for use where signal shielding caused by a steel building or any other facility where a lack of windows is prevalent.

### Wiring requirement:

Coaxial provided

### Terminal plug:

2 Position Dual Direction slide in plug

### Mounting type:

Wall mount

### Cable length:

10'

### Dimensions:

Height: 4 1/2"  
Width: 2 7/8"  
Depth: 2 3/8"

### Operating temp:

-13 deg F to + 149 deg F

ZAP Controls  
840 Plug In Receiver/2416 Internal Antenna/2414 External Antenna

840 2416 2414 USA

### ZAP Series 3

## Simply Logical

ZAP Controls  
100 Waterloo Blvd. Anglesey Business Park, Littleworth Road, Cannock, Staffordshire, England  
UK Office Number 011-44-154-387-9444 sales@zap-uk.com  
USA Contact 931-510-4432 sales@zap-america.com  
USA Tech Support 931-510-4432 via telephone or text  
Online www.zap-uk.com